

PowerWalker AVR 1000

Voltage Regulator

1000VA Voltage Regulator

3x Schuko output receptacles

Modem/Phone Surge Protection

Overload, short circuit and over-temperature protection

Compact size and stylist design



Item-No. 10120301



3x Schuko Outlets



AVR (Autom. Voltage Regulator)



Fax & Modem Security Port

Product Features

PowerWalker AVR 1000 is a voltage regulator which accepts wide input voltage range (180-264VAC). It provides stable output voltage through boost and buck stabilizer. The built-in thermal sensor provides over-temperature protection and recover, while abnormal situation is eliminated.

PowerWalker AVR 1000 includes a selectable Master/Slave function to reduce idle power wastage.

- Stylist design with colourful panels for your consideration
- 3 local receptacles for easy use
- Built-in thermal sensor for over-temperature protection and auto recovery system



3x Schuko outlets

Technical Details

Product Features

Capacity	1000VA/600W
-----------------	-------------

Input

Voltage	220/230/240VAC
Voltage Range	180-264VAC
Frequency Range	50Hz
Surge Rating (LV/HV)	430/250 Joules

Output

Voltage Regulation	± 12 %
AVR	± 8 %
Output Receptacles	3x Schuko

Protection

Short-Circuit	Yes
Over-temperature	Yes
Overload	Yes

Indicators

Power LED	Green lighting
AVR LED	Red lighting

Product Details

Dimensions	166mm x 161mm x 87mm (D x W x H)
Colour	Black
Weight	2.0kg
Model Code	AVR 1000

Environment

Temperature	0°C – 40°C
Humidity	0 - 90% (non-condensing)

Package Content

Package Content	PowerWalker AVR 1000, printed manual
------------------------	--------------------------------------

Logistic Data

Giftbox Language	EN/DE/FR/ES/IT/PT/SE/FI/NO/TR RU/UA/BY/PL/CZ/HR/HU/BG/KZ/CS
Manual Language	EN/DE/FR/ES/IT/PT/SE/FI/NO/TR RU/UA/BY/PL/CZ/HR/HU/BG/KZ/CS
Dimension/Giftbox	191mm x 119mm x 231mm (D x W x H)
Weight/Giftbox	2.2kg
Pieces/carton	9
Dimension/carton	601mm x 389mm x 261mm (D x W x H)
Weight/carton	20.4kg
Pieces/palette	288
BlueWalker Item-No.	10120301
EAN-Code	4260074973563
Warranty	24 Months

Version: EN 12/04/2011

We reserve the right for technical changes and mistakes